



The MicroJet™ is designed for blowing or floating telecommunication micro-cables (optical fibre, coax or multipair) in preinstalled ducts.



PR-196

PRM-196






Standard equipment:

- 1 box for the MicroJet and its accessories
- 1 set of tools
- 1 speed and distance indicator
- 1 air hose with quick release coupling Mody to connect the compressor
- 1 driving wheel without steel tyre
- 1 pressure wheel (aluminium)
- 1 bottle of lubricant Micro jetting lube
- 1 operation and maintenance manual

| Standard version | MicroJet | MicroJet |
|---|-----------------|-----------------|
| Type | PR-196 | PRM-196 |
| Cable dia. [mm] | 3.5-8.0 | 1.0-8.0 |
| Duct OD [mm] | 7.0-16 | 3.0-16 |
| Drive unit | Pneumatic | Pneumatic |
| Max. air consumption of motor [m3/min] | 0.2 (at 4 bar) | 0.2 (at 4 bar) |
| Pushing force [N] | 0-150 | 0-25 / 0-150 |
| Radial pressure on cable [N] | 15-180 | 15-180 |
| Max. speed [m/min] | 120 | 50 / 120 |
| Recommended speed [m/min] | 120 | 30-40 / 120 |
| Max. air pressure [bar] | 16 | 16 |
| Dimension of apparatus l x w x h [mm] | 285 x 250 x 255 | 285 x 250 x 335 |
| Dimension of apparatus with case l x w x h [mm] | 590 x 385 x 250 | 590 x 385 x 250 |
| Weight of machine [kg] | 5.6 | 6.7 |
| Total weight [kg] | 15.9 | 17 |

Specifications are subject to change without notice

Modular design according to the table below

| |  Pusher |  Magnetic clutch |  Pneumatic motor |
|---|---|--|--|
|  MicroJet PR-196 | X | | X |
|  MicroJet PRM-196 | X | X | X |

MAIN ACCESSORIES



Lubricator L9,
for the continuous lubrication of cables
for a better Jetting performance



Figaro / Figarino,
intermediate cable storage system,
avoiding figure of 8



Micro Jetting Lube,
lubricant improving Jetting performance